

# Toughpower Cable Management

**14cm Fan** **650W**

**ATX 12V 2.2 & EPS 12V**

**- Embedded Socket and  
Modularized Cable Management -**



**Tt Thermaltake**  
COOL ALL YOUR LIFE

[www.thermaltake.com](http://www.thermaltake.com) [thermaltake@thermaltake.com](mailto:thermaltake@thermaltake.com)

©2006 Thermaltake Technology Co., Ltd. All Rights Reserved.



# Manual



# Table of contents

<b>1. Introduction</b> .....	<b>01</b>
<b>2. Components Check</b> .....	<b>04</b>
<b>3. Installation</b> .....	<b>05</b>
<b>3.1 Warnings and Cautions</b> .....	<b>06</b>
<b>3.2 Embedded Socket and Modularized Cable Management</b> .....	<b>06</b>
<b>3.3 Installation Steps</b> .....	<b>07</b>
<b>3.4 Power Supply Installation</b> .....	<b>08</b>
<b>4. Product Specification</b> .....	<b>12</b>
<b>4.1 Output Specification</b> .....	<b>12</b>
<b>4.2 Toughpower 650W Power Supply</b> .....	<b>15</b>
<b>4.3 Other Specification</b> .....	<b>17</b>
<b>4.4 Protection</b> .....	<b>17</b>
<b>4.5 Environment</b> .....	<b>18</b>
<b>4.6 Hi-Pot (Input / Output isolation)</b> .....	<b>18</b>
<b>4.7 CE Requirements</b> .....	<b>18</b>
<b>5. Trouble Shooting</b> .....	<b>19</b>
<b>6. Cable Retail Package</b> .....	<b>20</b>

## 1. Introduction

We live up to the promise of Thermaltake logo in our unending quest for excellence.

Shall you have any suggestion or comments, please access our web site :

<http://www.thermaltake.com>

or e-mail to :

[thermaltake@thermaltake.com](mailto:thermaltake@thermaltake.com)

we appreciate your kindly feedback and you will receive the prompt response from our customer service team.

Thank you for choosing a quality Thermaltake Toughpower 650W Cable Management PC Power Supply. The Toughpower 650W featuring our Embedded Socket and Modularized Cable Management plus 14cm cooling fan. We trust that you will find it providing you with many years of service.

Thermaltake Technologies delivers most solid line of power supplies built to specifically towards high-end systems for utmost PC system performance. The leader in thermal solutions defines Tough as being "able to withstand great strain and stress without tearing or breaking" same with their newest and latest line of ToughPower power supplies.

-Independent voltage circuit

Voltage won't fluctuate and influence each rails. The particular design for +3.3V, +5V, and +12V that offers unflappable current delivery under heavy load and makes voltage output more stable.

-Extremely good voltage regulation ( $\pm 3\%$ )  
 Most power supplies has only one group regulation choke with three windings. However, the Toughpower takes on a different approach. The three (+3.3V, +5V, +12V) rails are all separate rails with individual windings. This feature allows the rails to have a tighter load regulation (3% or better) than the other power supplies. This feature also helps system voltage stay steady.

-Industrial grade components (capacitor, transformer, etc)  
 The key feature of the Toughpower is the usage of the highest quality components possible. Therefore, Toughpower allows the users to enjoy performance without worrying about the reliability.

-High reliability: MTBF > 120,000 hours  
 Toughpower features an extremely long MTBF (Mean Time Between Failures): 120,000 hours; which goes above and beyond all ATX specifications.

-Extended warranty: 3 years  
 With our high quality and solid circuit designs, we are confident to provide three years of warranty instead of the one-year industrial standard period.

Please take the time in familiarize yourself with the power supply, its connectors and the contents of this manual before proceeding with the installation of the power unit. You will need a Phillips crosshead screwdriver, perhaps your PC case manual and most certainly your motherboard manual.

**S**hould you have any questions regarding the aforementioned steps, please contact Thermaltake directly. Failure to follow the proper procedures may cause severe bodily harm or PC component damage.

For Support or General Inquiries, please contact us at:

#### ***Thermaltake Technology USA***

Toll Free: (800)988-1088

Email: support-usa@thermaltake.com

#### ***Thermaltake Europe B.V.***

Tel:+31-10-409-0150

Email: johnnyhsu@thermaltake.com.tw

#### ***Thermaltake Beijing Co.Ltd.***

Tel:+86-10-82883159/3189 ext.16

Email: doctort@thermaltake.com.cn

#### ***Thermaltake Australia and New Zealand Pty Ltd***

Tel:+613-9763-1622

Email: sales@thermaltake.com.au

#### ***Thermaltake Japan Inc.***

Email: sales-jp@thermaltake.co.jp

## 2. Components Check

1

650W power supply unit  
(With one 24-pin main power connector & one 6-pin PCI-Express connector)



2

A 4+4-pin +12V power connector



3

Two sets of wires with 4-pin peripheral power connector



4

Two sets of wires with 4-pin floppy drive connector



5

Two sets of wires with 6-pin PCI-Express power connector



6

Two sets of wires with 5-pin SATA connectors



7

One AC input power cord



8

4 mounting screws



9

User manual



## 3. Installation

### 3.1 Warnings and Cautions


- 3.1.1 Do not pull the AC power cord when the power supply is in use or else damage to components will result.
- 3.1.2 Do not store the Power Supply in a high humidity and high temperature environment.
- 3.1.3 When using an ATX type power supply under testing conditions where the power supply unit is not installed in a PC with its components, please follow the steps below:
- 1) Please take a paper clip and untwist it.
  - 2) Make sure the power supply unit is in the "OFF" position.
  - 3) Locate the 20 or 24 pin motherboard connector from the power supply unit.
  - 4) Plug one side of the paper clip into the green wire hole.
  - 5) Plug the other side of the paper clip into any of the black wire holes.
  - 6) Turn on the PSU to see if the power supply fans turn on.
- 3.1.4 High voltages exist in the power supply. Do not open the power supply case unless you are an authorized service technician or electrician.
- 3.1.5 All warranties and guarantees shall be voided should there be a failure to comply with any of the warnings and cautions covered in this manual.

### 3.2 Embedded Socket and Modularized Cable Management

#### 3.2.1 Embedded Socket and Modularized Cable Management:

The new embedded socket and modularized cable management allows user use only the cables they need and improve the airflow in the chassis.

#### Embedded Socket and Modularized Cable Management Design:



3.2.2 Toughpower 650W unit: On the power supply, you will find sockets to connect with those cables. Users can choose which wire set they want to use for devices, graphic card, fans, etc. Inside the package, you will find the following wire set:

1. One 4+4 pin +12V connector
2. Seven 4-pin peripheral power connectors and two 4-pin floppy drive connectors
3. Six 5-pin S-ATA connectors
4. Two 6-pin PCI-Express graphic card connectors

### 3.3 Installation Steps

To prevent electrical shocks, please disconnect the power cord from your existing power supply unit. Toughpower 650W Cable Management PSU has automatic Voltage Selector Which will automatically change to 100V-240V PSU .

#### Installation Steps

- 3.3.1 Ground yourself to remove any static electricity by briefly touching your PC cases and then, disconnect the power cord from your old power supply (if replacing it)
- 3.3.2 Follow your computer case manual and disassemble the case.
- 3.3.3 Disconnect all the power connectors from the motherboard and from the peripheral devices such as case fans, hard drives, floppy drives. etc.
- 3.3.4 Remove the existing power supply from your computer case and replace it with your new Thermaltake **Toughpower 650W Cable Management** PSU.
- 3.3.5 Connect the power connectors to the motherboard and peripheral devices (refer to the rest of this manual to match the various one-way key-locked connectors to the motherboard and accessories).
- 3.3.6 Connect the 6-pin PCI Express connector to PCI Express graphic card if you need.


Note: Please read the user manual supplied with your graphic card for detail usage instructions.

- 3.3.7 Close the computer case.
- 3.3.8 Make sure your power supply switch is on "OFF" position, and connect the supplied power cord to your Thermaltake **Toughpower 650W Cable Management** PSU.

### 3.4 Power Supply Installation


#### Step 1

After install the power supply unit into the chassis and then connect the 20+4-pin main power cable to motherboard 20pin or 24 pin socket.



#### Step 2

Connect the 4+4-pin +12V auxiliary power connector to the motherboard. (Users can use either 4 pins or 8 pins, depending on the motherboard. Please check with the motherboard user's manual.)



#### Step 3

**Note:** Please check the below information before install your Dual PCI-Express graphic cards.

The Toughpower 650W Cable Management Power Supply has three PCI-Express connectors. One of the PCI-Express connectors comes out directly from the power supply unit, the other two PCI-Express connectors are modularized design.


For the below SLI and CrossFire dual graphic card mode, you have to use one PCI-Express connector which comes out from the power supply unit and one modularized PCI-Express connector for best performance and stability.

NVIDIA SLI Card	ATI CrossFire Card
GeForce 7900 GTX	Radeon X1900 series
GeForce 7900 GT	Radeon X1800 series
GeForce 7800 GTX 512MB	Radeon X1600 series
GeForce 7800 GTX 256MB	Radeon X1300 series
GeForce 6800 Ultra	
GeForce 6800 GT	
GeForce 6800	


**\*Please check Thermaltake website for installation instruction on future graphic cards.**

For other entry level SLI or CrossFire graphic cards, you can use two 6-pin modularized PCI-Express connectors.


First, high-level SLI or CrossFire dual graphic card mode installation: Connect the PCI-Express connector which comes out from power supply unit and one 6-pin modularized PCI-Express connector to your dual graphic cards.




Second, entry-level SLI or CrossFire dual graphic card mode such as NVIDIA 6600 series and ATI X850 series installation:  
Connect the two 6-pin modularized PCI-Express connector to your dual graphic cards.

**Step 4**

Connect the 4-pin power connectors to peripherals such as DVD burners, hard disk drives, etc. In addition, users can connect the 4-pin floppy power connectors to the floppy drive.



If there are S-ATA hard disk drives present, there are also Serial ATA connectors available.

**Step 5**


The whole power supply components inside the chassis.



## 4. Product Specification


### 4.1 Output Specification

#### Main Power Connector




Voltage	Color		Color	Voltage	
+3.3 V	Orange	1	13	Orange	+3.3 V
+3.3 V	Orange	2	14	Blue	-12 V
COM	Black	3	15	Black	COM
+5 V	Red	4	16	Green	PS_ON#
COM	Black	5	17	Black	COM
+5 V	Red	6	18	Black	COM
COM	Black	7	19	Black	COM
PWR_ON	Gray	8	20	N/C	N/C
+5 Vsb	Purple	9	21	Red	+5 V
+12 V <sub>1</sub>	Yellow	10	22	Red	+5 V
+12 V <sub>2</sub>	Yellow	11	23	Red	+5 V
+3.3 V	Orange	12	24	Black	COM

#### +12V Connector (4+4 pin)




Color	Signal	Pin
Black	COM	1
Black	COM	2
Black	COM	3
Black	COM	4
Yellow	+12VDC	5
Yellow	+12VDC	6
Yellow	+12VDC	7
Yellow	+12VDC	8

#### Peripheral Connector (4 pin)




Color	Signal	Pin
Yellow	+12V <sub>1</sub> DC	1
Black	COM	2
Black	COM	3
Red	+5VDC	4

#### PCI Express Connector (6 pin)



Color	Signal	Pin
Yellow	12VDC	1
Yellow	12VDC	2
Yellow	12VDC	3
Black	COM	4
Black	COM	5
Black	COM	6


#### Floppy Disk Connector (4 pin)



Color	Signal	Pin
Red	+5VDC	1
Black	COM	2
Black	COM	3
Yellow	+12V <sub>1</sub> DC	4

ATX 12V 2.2 &amp; EPS 12V Version

## Serial ATA Power Connector (5 pin)



Color	Signal	Pin
Yellow	+12V,DC	1
Black	COM	2
Red	+5VDC	3
Black	COM	4
Orange	+3.3 VDC	5

ATX 12V 2.2 &amp; EPS 12V Version

## 4.2 Toughpower 650W PSU Specification

## Features:

- Complies with ATX 12V 2.2 & EPS 12V version.
- Modularized Cable Management to eliminate clutter and improve airflow inside the case.
- SLI, CrossFire , and Dual Core CPU ready.
- Next generation four +12V rails(12V1, 12V2, 12V3, 12V4) supports high-end graphic card and PC system (combined loading of 52A).
- Independent Voltage Circuit: offers unflappable current delivery under heavy load and makes voltage output more stable.
- Active Power Factor Correction (PF>0.99) and high efficiency (up to 85%).
- Extremely good voltage regulation ( $\pm 3\%$ ): provides steady voltage for system.
- Industrial grade components (capacitor, transformer, etc)
- High reliability: MTBF>120,000 hours.
- Mirror effect housing and reliable 14cm ball-bearing fan.
- Protections: Over Current, Over Voltage, and Short-Circuit protection.
- Safety / EMI Approvals: CE, CB, TUV, FCC, UL, CUL, and BSMI certified.

SPECIFICATION	
P/N	W0128
Maximum Power	650 Watts
Color	Black
Switches	ATX Logic on-off additional power rocker switch
PFC (Power Factor Correction)	Active PFC
Cooling System	14cm Fan SPEED: 1900 RPM(+10%~-10%) DIMENSION: 140 X 140 X 25 mm AIR FLOW: 82 CFM TEMP. AUTO CONTROL
Noise	16 dBA at 1300 RPM
P. G. Signal	100-500 ms
Over Voltage Protection Recycle AC to Reset	+5V 7.0 Vmax +3.3V 4.5 Vmax +12V 15.6 Vmax
DIMENSIONS	
Unit Size	16cm(L)x15cm(W)x8.5cm(H)
Net Weight	2 kg
INPUT	
Input Voltage	100VAC - 240VAC
Input Frequency Range	47 - 63 Hz
Input Current	115VAC / 8A max. 230VAC / 4A max.
Hold-up Time	16 ms
Efficiency	up to 85%



ATX 12V 2.2 &amp; EPS 12V Version

## ► Total Output Connector



## ► Technology Features



## ► Cable Application



### Intelligent Cable Management:

- All cables with black cable sleeving
- Optimum air-flow in the chassis

OUTPUT								
Voltage	+3.3V	+5V	+12V <sub>1</sub>	+12V <sub>2</sub>	+12V <sub>3</sub>	+12V <sub>4</sub>	-12V	+5VSB
Max. Load	30A	28A	18A	18A	18A	18A	0.8A	3.0A
Min. Load	0.5A	2.0A	1.0A	1.0A	1.0A	1.0A	0A	0A
Peak Load	-	-	-	-	-	-	-	3.5A
Load Reg.	+3% -3%	+3% -3%	+3% -3%	+3% -3%	+3% -3%	+3% -3%	+9% -5%	+5% -3%
Ripple & Noise	50 mV	50 mV	120 mV	120 mV	120 mV	120 mV	120 mV	50 mV

ATX 12V 2.2 &amp; EPS 12V Version

## 4.3 Other Specification

- 4.3.1 Inrush Current:  
55A max. when AC input 115Vac at 25°C cold start.  
110A max. when AC input 230Vac at 25°C cold start.
- 4.3.2 Power Efficiency:  
80% (min.) up to 85%  
115VAC - Full load 80%  
230VAC - Full load 85%
- 4.3.3 Power Factor:  
PF>0.9
- 4.3.4 Note:  
The continuous total output power is 650W max.  
The combined power of +5V and +3.3V is 180W max.  
Peak currents may last up to 12 seconds with not more than one occurrence per minute.  
Total combined +12V output load not exceed 52A.
- 4.3.5 Hold-Up Time:  
16msec (minimum) at 80% of full load at 230Vac input.
- 4.3.6 Power Good Delay:  
100-500 msec.
- 4.3.7 Power Fail Delay:  
> 1 msec.
- 4.3.8 Turn-On Delay Time:  
2000 msec max.
- 4.3.9 Rise Time:  
20ms max at full load.

## 4.4 Protection

When OCP, OVP or short protection is triggered, the main outputs will be latched off. The main outputs can be reset by cycling the DC remote on/off or AC power. +5Vsb output is auto recovery when fault condition removed.

- 4.4.1 Over Current Protection  
Not over 240VA for every output voltage.
- 4.4.2 Over Voltage Protection  
+3.3V output 4.5 Vmax  
+5.0V output 7.0 Vmax  
+12.0V output 15.6 Vmax

- 4.4.3 Short Protection  
All output to GND.

#### 4.5 Environment:

- 4.5.1 Operating Temp. 10°C to +50°C (+50°C for 750W series)  
4.5.2 Storage Temp. -20°C to +70°C  
4.5.3 Operating Humidity 20% to 90%, non-condensing  
4.5.4 Storage Humidity 5% to 95%, non-condensing  
4.5.5 Operating Altitude 0 to 10,000 feet  
4.5.6 Storage Altitude 0 to 50,000 feet

#### 4.6 Hi-Pot: (Input/Output isolation)

- 4.6.1 Primary to Secondary  
4242Vdc for 1 minute  
4.6.2 Insulation Resistance  
Primary to earth ground 500Vdc, 50M ohms Min.

#### 4.7 CE Requirements

- 4.7.1 Conducted EMI  
1. Meet FCC: Class B  
2. Meet CISPR 22: Class B  
3. Meet BSMI: Class B  
4.7.2 Safety Standards  
1. Meet CUL (UL 60950)  
2. Meet TUV EN60950  
3. Meet CB (IEC 950)  
4. Meet CE  
5. Meet CCC  
4.7.3 Harmonic  
Meet IEC1000-3-2, Class D  
4.7.4 MTBF at 25°C(demonstrated)  
Over 120K hrs

## 5. Trouble Shooting

### Condition 1:

No DC output. The fan or fans are motionless

1-1 Is the AC inlet plug firmly plugged into the PSU inlet socket?

1-2 Is the wall socket, extension power cord, power strip or surge protector in use, fully functional and wall power switch turned 'ON'?

1-3 Is the Main Board socket (24pin) plug fully and firmly inserted?

### Condition 2:

The fan or fans began rotating and then stopped. The system hangs without proceeding any further.

Check:

2-1 Are the peripheral connectors firmly plugged into accessory devices, such as the main hard drive, CD ROM, etc?

2-2 If a plug has been inadvertently connected in an off-set or reversed position, unplug the AC power source, reconnect the offending connectors and then wait for 30 seconds before replug in the AC power source and try again.

### Note:

If the power supply still cannot or is still unable to power up after following the above instruction, please send the unit back to your dealer or retailer for after sales service.

## 6. Cable Retail Package(Optional)

### P/N:A2169 PSU Adaptor Cable Specification

	<b>(A)</b>	<b>(B)</b>
<b>Model</b>	<b>Adaptor Cable</b>	<b>Adaptor Cable</b>
<b>Dimension (mm)</b>	<b>193mm</b>	<b>198mm</b>
<b>Connector type</b>	<b>4pin - 8pin</b>	<b>20pin - 24pin</b>
<b>Cable sleeving color</b>	<b>Red</b>	<b>Black</b>
<b>Material</b>	<b>Plastic</b>	<b>Plastic</b>
<b>Weight</b>	<b>16 g</b>	<b>58 g</b>
<b>Voltage</b>	<b>12 V</b>	<b>3.3V,5V,+12v,-12V</b>

**(A)4pin-8pin****(B)20pin-24pin**

## Note

---